WEMS Electronics



EMI Filter Connectors and Inserts

www.wems.com | (310) 644-0251

WEMS Electronics

Company Overview

Established in 1959, WEMS Electronics is a full service turn-key Veteran-Owned Small Business (VOSB) with an extensive AS9100:D / ISO 9001:2015 registered complex specializing in state-of-the-art EMI custom filters, engineering and manufacturing services. We are one of the few companies that offer a completely integrated approach to the design and fabrication of precision electronic components, assemblies and subsystems. In addition, our EMI/RFI filter division manufactures high reliability multi-circuit & discreet feed-through (F/T) input, output, power and signal line filters for military, aerospace, space, and commercial applications.

Our EMI filter division specializes in engineering services and includes:

- EMI Filter Design
- EMI Filter Circuit Analysis
- EMI Filter & Power Magnetics Design
- Magnetics Analysis
- EMI Filter Circuit Lay-Out and Packaging
- EMI Filter Source / Specification Control Drawings
- Acceptance Test Procedures
- Qualification Test Procedures
- Base Line Documentation



For practical reasons, it is impossible to include in our capability brochures all the designs we have created. However, WEMS specializes in developing unique filters, electronic assemblies & systems for nonstandard applications. We are ready to solve your most challenging requirements and would welcome any opportunity to demonstrate our expertise on your new & upgrade program requirements.

WEMS is committed to providing a wide range of state-of-the-art engineering and innovative manufacturing services and high quality products delivered on time with superior value while always conducting our business in a responsible and ethical manner. We pledge to our customers and to each other that we will continually improve our level of customer satisfaction through our commitment to excellence.







Why do you need an EMI Filter?

Electromagnetic compatibility (EMC) engineers use the concept of "noise" to describe the unwanted signals that degrade the performance of electronic equipment. In avionic applications, both external and internal sources of EMI noise can jam sensitive navigation and tactical equipment, possibly even disrupting control of the aircraft. An aircraft carrier's massive electronics bay might cause interference that scuttles a take-off or landing. EMI affecting satellite transmissions can cause communication failures on the battleground. For these reasons, EMI is considered a serious problem, and numerous technologies and techniques have been developed to insure electromagnetic compatibility (EMC) in data transmission systems—from shipboard to undersea, from avionics to space, from aircraft carriers to micro unmanned aerial vehicles.

Sources of EMI

Sources of EMI "noise" can be grouped into three categories: 1) Intrinsic noise that arises from random fluctuations within physical systems, such as thermal and shot noise, 2) Man-made noise from motors, switches, power supplies, digital electronics and radio transmitters, and 3) Noise from natural disturbances such as electro-static discharge (ESD), lightning and sunspots.

Intrinsic

Intrinsic noise sources can be very subtle and often go unrecognized. All electrical systems are potential sources of intrinsic noise, including such common devices as portable radios, MP3 players, cell phones and so on. These devices can cause interference simply by being on. This is because electrons within a conducting media or a semiconductor device create current flow when excited by external voltages. When the externally applied voltage stops, electrons continue to move, randomly interacting with other electrons and with the surrounding material. This random electron motion can create noise in conducting media even without current flow.

Man-made

To protect avionics systems from man-made noise, intentional radio frequency (RF) emitters like cell phones, Bluetooth accessories, CB radios, remote-controlled toys, and walkie-talkies are banned outright on commercial airline flights. Laptops, hand held scanners and game players, while not intentional emitters, can produce signals in the 1 MHz range that can affect performance of avionic equipment. Navigation cabling and other critical wiring runs along the fuselage with passengers sitting just a few feet away. Since the thin sheet of dielectric material that forms the interior of the passenger compartment— typically fiberglass—offers no shielding whatsoever; and since commercial passenger jets contain up to 150 miles of electrical wiring that can behave like a giant antenna, it is extremely important for passengers to heed regulations on the use of potentially disruptive electronic equipment.

Obviously, these internal sources of EMI are quite dangerous to aircraft because they are so close to the systems they might affect. But external sources, such as radio and radar transmitters on the ground, or radar from a passing military plane, cockpit avionics are susceptible to multiple sources of EMI including man-made interference from iPhones® and other PEDs can be even more disruptive due to the high power and frequency of such equipment. As if the many external and internal sources of EMI were not enough of a concern, the aluminum airframe itself, in certain circumstances, can act as a resonant cavity in the 1 to 10 MHz range. Behaving much like a satellite dish, the airframe can compound the effects of both internal and external EMI by concentrating man made and naturally-occurring transient signals and broadcasting the interference into nearby equipment. A recently released report from a major aircraft manufacturer illustrates the ongoing concern with passenger-carried portable electronic devices (PED). The number of these devices on commercial airplanes has mushroomed, particularly with the advents of new classes of laptop devices such as the Apple iPad. The use of PEDs produces uncontrolled electromagnetic emissions that have the potential to interfere with avionic systems. While aircraft avionics gear is tested and qualified to rigorous electromagnetic standards PEDs are not subjected to even a fraction of the same testing and qualification regimens for electromagnetic compatibility. As system speeds have increased, the voltage levels of data signals have necessarily decreased, making them much more susceptible to performance degradation by unwanted electronic noise—particularly the combined noise of large numbers of PED's operating within a single aircraft.

The frequency bands used by avionic systems span the electromagnetic spectrum from a few kilohertz to several gigahertz. At the low end, Omega Navigation, which is used to fix aircraft position within a network of ground based transmitters, operates in the frequency range of 10 to 14 KHz. VHF Omnidirectional Range Finders (VOR) are radio beacons used in point to point navigation. They operate from 108 to 118 MHz. Glideslope Systems used during landings operate in the 328 to 335 MHz range. Distance-Measuring Equipment (DME), which gauges the space between the aircraft and ground-based transponders operate at just over 1 GHz. Also in the spectrum above 1 GHz are global positioning, collision avoidance, and cockpit weather radar systems. Personal Electronic Devices (PEDs) operate at frequencies from 10 to 15 KHz for AM radios and up to 400 MHz for laptop computers. When the higher harmonics of these signals are taken into account, the emitted frequencies cover almost the entire range of navigation and communication frequencies used on the aircraft, and PEDs, are just a single class of EMI emitters. When the full spectrum of other radiated and conducted EMI emitters are taken into account, it becomes clear that the entire system of electronic equipment aboard commercial and military aircraft are at risk to EMI.

Naturally

Naturally occurring noise sources such as ESD, lightning or other energy surges also present significant life safety and equipment damage potential. A poorly grounded device can transmit dangerous energy from a transient surge to a technician, user or any other passerby. Sensitive semiconductors and other components can be damaged or destroyed. Solutions to naturally occurring noise include:

- Eliminate static buildup at the source
- Insulate the device properly
- Provide an alternative path for the discharge or surge to bypass the circuit
- Use of EMI Filters with Transient Suppression


In conclusion, it is becoming more and more apparent that EMI/EMC is a growing concern for both the military and commercial industries for all forms of electronic equipment. In response to the increasing demand for low-cost and effective EMI/EMC solutions, WEMS Electronics is here to solve your most challenging requirements and would welcome any opportunity to demonstrate our expertise on your new & upgrade program requirements.

Why use a Filter Connector or Insert?


Filters can be a planned addition to an electronic subsystem or, as frequently occurs, added after a problem has been discovered.

- Easiest and most cost effective permanent EMI/EMP solution – eliminate conducted EMI before it passes into the box
- Helps reduce volume inside the unit as well as conserve circuit board space
- Moves filtering away from sensitive board electronics
- Can easily replace existing non-filtered connectors in existing systems
- Mates with standard Mil-Spec connectors: MIL-DTL-38999, MIL-DTL-26482, MIL-DTL-83723, MIL-DTL-26500, AS50151, MIL-DTL-24308, MIL-DTL-83513, etc.
- Meets military standards and aerospace environmental requirements: EIA-364, MIL-STD-810, MIL-STD-461, DO-160, etc.


Types of Filtered Connectors and Their Performance




	Capacitance Options	Filter Performance
Chip Capacitor	3 pF – 47,000 pF+	>40 dB
Discoidal Capacitor (C)	470 pF – 40,000 pF+	50 – 60 dB
Planar Array (CL & LC)	100 pF – 1 uF+	50 – 60 dB
Pi with Planar Arrays	100 pF – 1 uF+	70+ dB
Pi Tubes	47 pF – 12,000 pF	70+ dB




Chip Capacitor Filter Performance




Chip Cap Assembly




Pi Tube Assembly




Pi Filter Construction with Planar Array



Pi Type Planar Array Assembly



Pi Tube Contact Assembly



Chip Capacitor Filtering
- 40+ dB Insertion Loss
- Quick Turn
- Lowest Cost Option
- Limited High Frequency Performance

Termination Options:
- Solder Cup
- PC Tail
- Wired terminations

C, C-L or L-C Filtering
- Built with Chip Caps, Discoidals, Planars or C Tubes
- 45 - 60 dB Insertion Loss
- Good Broad Spectrum Filter Performance

Pi Filtering
- Built with Pi Tubes, Discoidal or Planar Arrays
- Provides C-L-C Component Configuration
- Highest Performance: 70+ dB Insertion Loss
- Very Good High Frequency Performance

Other Options:
- Custom versions available including the ability to define the Filtering on a Pin by Pin basis to help eliminate as much noise as possible from your system
- Combination of filtering and transient suppression components available
- Custom applications and Filter Modules available to meet your special requirements

EMI Filter Connectors and Inserts

Filtered MIL-DTL-38999 Connector Part Number Builder

W C 7F 15-35 P S N C B 5-473

WEMS Electronics

MIL-DTL-38999 TYPE
- SERIES I **A**
- SERIES II **B**
- SERIES III **C**

MOUNTING STYLE
- WALL MOUNT **0**
- BOX MOUNT **1**
- JAM NUT **4**
- SOLDER MOUNT **5**
- PLUG **6**
- WELD MOUNT **7**

FINISH
- ELECTROLESS NICKEL **F**
- OD CAD **W**
- other finishes available, consult factory

SHELL SIZE AND INSERT ARRANGEMENT (PER MIL-STD-1560)
example:
15-35

CONTACT GENDER
- MALE PINS **P**
- FEMALE SOCKETS **S**

CONTACT TERMINATION
- PC TAIL **P**
- SOLDER CUP **S**
- WIRE TERMINATION **W**

CONNECTOR POLARIZATION
N, A, B, C, D, E

CAPACITANCE (3 DIGIT)
EXAMPLES:
- **221** 220 pF
- **682** 6,800 pF
- **473** 47,000 pF

VOLTAGE RATING (STEADY STATE)
- **0** 50 VDC
- **1** 100 VDC
- **2** 200 VDC
- **3** 300 VDC
- **4** 400 VDC
- **5** 500 VDC

for values over 500, consult factory

FILTER LOCATION
- **S** SHELL EXTENSION (AS REQUIRED)
- **B** BACKSHELL COMPATIBLE

FILTER TYPE
- **C** CHIP CAPACITOR
- **D** DISCOIDAL / TUBULAR CAPACITOR
- **P** PI FILTER



Filtered MIL-DTL-26482 Connector Part Number Builder

W D 4W 10-98 P S N C B 5-473

WEMS Electronics

MIL-DTL-26482 TYPE
- SERIES I **D**
- SERIES II **E**

MOUNTING STYLE
- WALL MOUNT **0**
- BOX MOUNT **1**
- JAM NUT **4**
- SOLDER MOUNT **5**
- PLUG **6**
- PLUG, RFI **7**
- NARROW FLANGE MOUNT **8**
- WIDE FLANGE MOUNT **9**

FINISH
- ELECTROLESS NICKEL **F**
- OD CAD **W**
- other finishes available, consult factory

SHELL SIZE AND INSERT ARRANGEMENT (PER MIL-STD-1669)
example:
10-98

CONTACT GENDER
- MALE PINS **P**
- FEMALE SOCKETS **S**

CONTACT TERMINATION
- PC TAIL **P**
- SOLDER CUP **S**
- WIRE TERMINATION **W**

CONNECTOR POLARIZATION
N, W, X, Y, Z

CAPACITANCE (3 DIGIT)
EXAMPLES:
- **221** 220 pF
- **682** 6,800 pF
- **473** 47,000 pF

VOLTAGE RATING (STEADY STATE)
- **0** 50 VDC
- **1** 100 VDC
- **2** 200 VDC
- **3** 300 VDC
- **4** 400 VDC
- **5** 500 VDC

for values over 500, consult factory

FILTER LOCATION
- **S** SHELL EXTENSION (AS REQUIRED)
- **B** BACKSHELL COMPATIBLE

FILTER TYPE
- **C** CHIP CAPACITOR
- **D** DISCOIDAL / TUBULAR CAPACITOR
- **P** PI FILTER



Filtered MIL-DTL-83723 Connector Part Number Builder

W F 0 W 1 4 - 0 7 P S N C B 5 - 4 7 3

WEMS Electronics
MIL-DTL-83723 TYPE
SERIES III THREADED **F**
SERIES III BAYONET **G**
MOUNTING STYLE
SINGLE HOLE MOUNT **0**
FLANGE MOUNT **1**
SOLDER MOUNT **5**
PLUG PUSH-PULL **3**
PLUG **6**
PLUG RFI **7**
FINISH
ELECTROLESS NICKEL **F**
OD CAD **W**
other finishes available, consult factor
SHELL SIZE AND INSERT ARRANGEMENT (PER MIL-STD-1554)
example:
14-07
CONTACT GENDER
MALE PINS **P**
FEMALE SOCKETS **S**
CONTACT TERMINATION
PC TAIL **P**
SOLDER CUP **S**
WIRE TERMINATION **W**
CONNECTOR POLARIZATION
N, 6-9, Y

CAPACITANCE (3 DIGIT)
EXAMPLES:
221 220 pF
682 6,800 pF
473 47,000 pF
VOLTAGE RATING (STEADY STATE)
0 50 VDC
1 100 VDC
2 200 VDC
3 300 VDC
4 400 VDC
5 500 VDC
for values over 500, consult factory
FILTER LOCATION
S SHELL EXTENSION (AS REQUIRED)
B BACKSHELL COMPATIBLE
FILTER TYPE
C CHIP CAPACITOR
D DISCOIDAL / TUBULAR CAPACITOR
P PI FILTER



Filtered MIL-DTL-26500 Connector Part Number Builder

W H 1 A 1 4 - 0 7 P S N C B 5 - 4 7 3

WEMS Electronics
MIL-DTL-26500 TYPE
THREADED **H**
BAYONET **J**
MOUNTING STYLE
SINGLE HOLE MOUNT **0**
FLANGE MOUNT **1**
SOLDER MOUNT **5**
PLUG **6**
FINISH
ANODIC **A**
CONDUCTIVE **C**
other finishes available, consult factory
SHELL SIZE AND INSERT ARRANGEMENT (PER MIL-STD-1554)
example:
14-07
CONTACT GENDER
MALE PINS **P**
FEMALE SOCKETS **S**
CONTACT TERMINATION
PC TAIL **P**
SOLDER CUP **S**
WIRE TERMINATION **W**
CONNECTOR POLARIZATION
N, 6-9, Y

CAPACITANCE (3 DIGIT)
EXAMPLES:
221 220 pF
682 6,800 pF
473 47,000 pF
VOLTAGE RATING (STEADY STATE)
0 50 VDC
1 100 VDC
2 200 VDC
3 300 VDC
4 400 VDC
5 500 VDC
for values over 500, consult factory
FILTER LOCATION
S SHELL EXTENSION (AS REQUIRED)
B BACKSHELL COMPATIBLE
FILTER TYPE
C CHIP CAPACITOR
D DISCOIDAL / TUBULAR CAPACITOR
P PI FILTER



Filtered AS50151 Connector Part Number Builder

W M 1 F 1 4 - 0 3 P S N C B 5 - 4 7 3

WEMS Electronics

AS50151 TYPE
SERIES I **K**
SERIES II **L**
SERIES III **M**

MOUNTING STYLE
WALL MOUNT **0**
BOX MOUNT **1**
JAM NUT **4**
SOLDER MOUNT **5**
PLUG **6**

FINISH
ELECTROLESS NICKEL **F**
OD CAD **W**
other finishes available, consult factory

SHELL SIZE AND INSERT ARRANGEMENT (PER MIL-STD-1651)
example:
14-03

CONTACT GENDER
MALE PINS **P**
FEMALE SOCKETS **S**

CONTACT TERMINATION
PC TAIL **P**
SOLDER CUP **S**
WIRE TERMINATION **W**

CONNECTOR POLARIZATION
W, X, Y, Z

FILTER TYPE
C CHIP CAPACITOR
D DISCOIDAL / TUBULAR CAPACITOR
P PI FILTER

FILTER LOCATION
S SHELL EXTENSION (AS REQUIRED)
B BACKSHELL COMPATIBLE

VOLTAGE RATING (STEADY STATE)
0 50 VDC
1 100 VDC
2 200 VDC
3 300 VDC
4 400 VDC
5 500 VDC
for values over 500, consult factory

CAPACITANCE (3 DIGIT)
EXAMPLES:
221 220 pF
682 6,800 pF
473 47,000 pF



Filtered MIL-DTL-24308 Connector Part Number Builder

W N F 1 5 M P N - C G 5 - 4 7 3

WEMS Electronics

MIL-DTL-24308 TYPE
STANDARD TYPE I **N**
HIGH DENSITY TYPE II **P**

FINISH
ELECTROLESS NICKEL **F**
OD CAD **W**
other finishes available, consult factory

PIN COUNT
STANDARD TYPE I
09, 15, 25, 37, 50
HIGH DENSITY TYPE II
15, 26, 44, 62, 78, 104

CONTACT GENDER
MALE PINS **M**
FEMALE SOCKETS **F**
MALE TO FEMALE ADAPTER **MF**

CONTACT TERMINATION
PC TAIL **P**
SOLDER CUP **S**
WIRE TERMINATION **W**
IDC CONNECTOR **D**
RIGHT ANGLE **R**

OPTIONAL HARDWARE
NO HARDWARE OR THREADED INSERT **N**
THREADED INSERT **T**
other options available, consult factory

CAPACITANCE (3 DIGIT)
EXAMPLES:
221 220 pF
682 6,800 pF
473 47,000 pF

VOLTAGE RATING (STEADY STATE)
0 50 VDC
1 100 VDC
2 200 VDC
3 300 VDC
4 400 VDC
5 500 VDC
for values over 500, consult factory

COMPLIANCE
G STANDARD FILTER
R RoHS COMPLIANT

FILTER TYPE
C CHIP CAPACITOR
D DISCOIDAL / TUBULAR CAPACITOR
P PI FILTER





Filtered MIL-DTL-83513 Connector Part Number Builder

W R F 1 5 M P T - C G 5 - 4 7 3

WEMS Electronics

MIL-DTL-83513 TYPE
MICRO-D **R**

FINISH
ELECTROLESS NICKEL **F**
OD CAD **W**
other finishes available, consult factory

PIN COUNT
9, 15, 21, 25, 31, 37, 51, 69, 100, 122

CONTACT GENDER
MALE PINS **M**
FEMALE SOCKETS **F**
MALE TO FEMALE ADAPTER **MF**

CONTACT TERMINATION
PC TAIL **P**
SOLDER CUP **S**
WIRE TERMINATION **W**
RIGHT ANGLE **R**

OPTIONAL HARDWARE
NO HARDWARE OR THREADED INSERT **N**
JACKPOST **P**
THREADED INSERT **T**
JACKPOT AND THREADED INSERT **W**

CAPACITANCE (3 DIGIT)
EXAMPLES:
221 220 pF
682 6,800 pF
473 47,000 pF

VOLTAGE RATING (STEADY STATE)
0 50 VDC
1 100 VDC
2 200 VDC
3 300 VDC
4 400 VDC
5 500 VDC
for values over 500, consult factory

COMPLIANCE
G STANDARD FILTER
R RoHS COMPLIANT

FILTER TYPE
C CHIP CAPACITOR
D DISCOIDAL / TUBULAR CAPACITOR
P PI FILTER



Circular Filter Inserts

W 3 8 9 9 9 R 1 5 - 3 5 G 5 - 4 7 3

WEMS Electronics

CONNECTOR SERIES
38999
26482
83723
26500
50151
other connector series available, consult factory

CONNECTOR TYPE
RECEPTACLE **R**
PLUG **P**

SHELL SIZE AND INSERT ARRANGEMENT
example:
15-35

CAPACITANCE (3 DIGIT)
EXAMPLES:
221 220 pF
682 6,800 pF
473 47,000 pF

VOLTAGE RATING (STEADY STATE)
0 50 VDC
1 100 VDC
2 200 VDC
3 300 VDC
4 400 VDC
5 500 VDC
for values over 500, consult factory

FILTER TYPE
G STANDARD FILTER with INSTALL GUIDE
R RoHS COMPLIANT FILTER WITH INSTALL GUIDE

D-Subminiature Filter Inserts

W N 1 5 G 5 - 4 7 3

WEMS Electronics

CONNECTOR SERIES
STANDARD TYPE I **N**
HIGH DENSITY TYPE II **P**

PIN COUNT
STANDARD TYPE I
09, 15, 25, 37, 50
HIGH DENSITY TYPE II
15, 26, 44, 62, 78, 104

CAPACITANCE (3 DIGIT)
EXAMPLES:
221 220 pF
682 6,800 pF
473 47,000 pF

VOLTAGE RATING (STEADY STATE)
0 50 VDC
1 100 VDC
2 200 VDC
3 300 VDC
4 400 VDC
5 500 VDC
for values over 500, consult factory

FILTER TYPE
G STANDARD FILTER with INSTALL GUIDE
R RoHS COMPLIANT FILTER WITH INSTALL GUIDE





WEMS Electronics

Phone: (310) 644-0251 | Fax: (310) 644-6957 | 4650 West Rosecrans Avenue | Hawthorne, CA 90250

www.wems.com